

MINI TIMER MT10



Versatile switch clock for manual or automatic remote control of Marmitek X-10 Modules. Ideal for simulating a presence in your house: it looks like you are always at home. Four different modules can be switched up to 4 times a day. Built-in alarm clock.

APPLICATION

The MT10E Mini Timer can be used to turn Marmitek X-10 Modules on or off at a pre-programmed time. Up to 4 modules can be pre-programmed with 2 'On' times and 2 'Off' times.

The buttons can be used to manually control 8 modules. These modules can be controlled using the Marmitek X-10 Commands 'On', 'Off' and 'Dim'. The MT10 also has buttons for 'All Lights On' and 'All Units Off'.

The mini timer has a 'Security' button, which randomly adjusts the pre-programmed times for the modules every day (up to 1 hour difference). If the lighting in the house is controlled using this method, the house always looks lived-in. The modules are controlled via the mains. No extra wiring required.

The mini timer also has an adjustable alarm clock, which can switch on a module. This means the lights can be switched on when the alarm goes off.

The 'Sleep' function turns the modules on or off at a specific time. This time can be adjusted in increments of 15 minutes.

The mini timer is powered via the mains. A back-up battery will retain the time and settings in case of a power failure.

MINI TIMER MT10



Power:	230V +10% -15%, 50Hz
Back-up battery:	9V PP9
Minimal Back-Up Power:	6V DC
Battery empty indicator:	7.5V +/-0.5V DC
Dimensions:	55x150x110mm
Weight:	590g
Colour:	Silver